

RS232 Command List for IFP UHD Series

Command Function	BYTE_0	BYTE_1	BYTE_2
POWER_Off	69	76	20
POWER_On	69	53	43
ENTER	69	07	8F
MUTE	69	37	5F
1	69	92	04
2	69	A2	F4
3	69	B2	E4
4	69	93	03
5	69	A3	F3
6	69	B3	E3
7	69	94	02
8	69	A4	F2
9	69	B4	E2
0	69	95	01
VOL+	69	82	14
VOL-	69	85	11
CH+	69	C4	D2
CH-	69	C5	D1
SOURCE	69	19	7D
MENU	69	80	16
LEFT	69	63	33
RIGHT	69	66	30
DOWN	69	43	53
UP	69	46	50
Get power status	79	33	53
Get source status	69	18	7E

Second Version

AV	89	55	0D	14
YPbPr	89	55	04	1D
VGA	89	65	03	0E
HDMI	89	65	0E	03
HDMI1	89	65	05	0C
HDMI2	89	65	07	0A
HDMI3	89	65	09	08
HDMI4	89	65	0B	06
OPS	89	65	0D	04
FREEZE	89	55	06	1B
Enter Android	89	65	06	0B
Exit Android	89	15	53	0E

Applicable for 2017 version of Android (with Android menu swap up from bottom) with following IFP EAN code:

55" IFP EAN: 8592580113215

65" IFP EAN: 8592580113222

75" IFP EAN: 8592580112638

86" IFP EAN: 8592580112645

In case you upgraded Android to the newest version with 2 touch Android gesture menu please use the updated command list for new 2018 version of Android.

Please note : BaudRate 38400 DataBit 8 StopBit 1 VerifyBit none